December 17, 1996

## ONCORE™ Active Antenna System

## Introduction:

Both the gain and the noise of the overall system affect the performance of the A/D convertor in a GPS receiver. The illustration below, shows typical values for the ONCORE™ family of GPS receivers when used with the Motorola antenna and standard RG-58 cable. The thresholds and ranges listed should be considered with a tolerance of 2 to 3 dB.

## **System Constraints:**

Gain: The gain in decibells is cumulative through all stages (i.e., G = G1 + G2 + G3 ...). The optimal gain of the antenna, cabling and any in-line amplifiers and splitters is 18 dB + or - 8 dB. The ONCORE receiver may operate outside of the optimal gain range but performance will degrade. Therefore, Motorola does not recommend operating outside of the optimal gain range.

For the system below, the gain is 18 dB in front of the receiver


Noise: System noise (F) is not to exceed 4 dB. The cascaded system noise figure formula is:

$$F = F1 + \frac{F2 - 1}{G1} + \frac{F3 - 1}{G1 \cdot G2} + \frac{F3 - 1}{G1 \cdot G2}$$

( = 2.7 dB for the system below)

Where F1 is the noise figure for stage one and G1 is the gain for stage one, etc. Note that all of these values are absolute. Recall the formula for converting absolute values to decibels:

$$F(dB) = 10 Log(F)$$



For configuration assistance, order placement and technical support call:



P.O. Box 262250 • San Diego, CA 92196 Phone: (619) 566-0666 • Fax: (619) 566-0768